

STEPHILL[®] GENERATORS

Designed and Built in the UK



Rating	Model	Engine
6.5KVA Petrol Generator	SE6500EC	POWERED by HONDA

GENERATOR SPECIFICATION	
Frequency	50Hz
Phase	Single
Voltage	110 / 55 CTE
Power	6.5kVA / 5.2KW
Alternator	NSM M100SG
Type	Brushless Maintenance Free
Regulation	Mechanical
Protection Class	IP23
Insulation Class	H
Fuel tank capacity	15.5
Autonomy 75% load	6.2hr
LWA	97
DBA @ 7M	72



ENGINE SPECIFICATION	
Engine	Honda GX390
Emissions	N/A
Distribution	O.H.V.
Cylinders	1
Cooling	Air
Start	Electric / Recoil
Fuel	Petrol unleaded
Rpm	3000
Oil Capacity (L)	1.1
Oil Alert/Low Oil Shutdown	Yes

DIMENSIONS (mm)			
Length	Width	Height	Weight KG
710	510	600	86

CONTROL BOX (METAL)
Push Button MCB Overload protection 2 x 110V 16A 1 x 110V 32A BS4343 Sockets

3 Year Engine Warranty (Limited)



OPTIONS
Trolley Kit
Long Run Fuel Tank

Stephill Generators Ltd reserve the right to change any of the characteristics stated without notice, in a constant effort to improve the quality of its product

Stephill Generators Ltd
Wallis Close
Park Farm South
Wellingborough
Northants
NN8 6AG

Phone : :+44 (0)1933 677911
Fax : :+44 (0)1933 677916
E-mail : info@stephill-generators.co.uk
Web : www.stephill-generators.co.uk

Date of Issue :- Sept 2015